

ZETA 12BT PROZETA SERIES

- Easy to transport
- Quick setup and tear down
- Suitable for DJs and travelling musicians



Technical Specification

System Type	Self Powered 12", 2-Way vented speaker with DSP
Max SPL Output	6 W, 100 V line transformer
LF Driver	12" Driver with 3" Voice Coil
HF Driver	1.3" Driver
Coverage Pattern	90°H x60 °V
Frequency Response (-6dB)	57Hz -20KHz
Crossover Frequency	1.6 KHz
Power Rating	830W (Program) 1660W (Peak)
Connectors	2 X Balanced XLR / 1/4 inch input, IX 3.5inch input/ XLR Link out
Media Player	Bluetooth / MP3 USB / SD Card
External Controls & Indications	Volume Controls on Input 1 & 2, Master Volume Control, 2 Band EQ, Green LED - Power ON, Red LED - Clip Indicator
Electronic Protections	Thermal/ Overload/ Limiter
Power Supply	110V - 120V / 220 -240V, 50/60 Hz
Suspension / Mounting	36mm pole socket, 4XM10 Suspension Points
Enclosure Construction	Trapezoidal Plastic Cabinet with Metal Grille, Rubber Feet, 3 x Handles (Top and sides)
Dimensions (HXWXD)	559 X 381 X 330 mm
Net Weight	14.3 Kg

For more information,

<https://honeywellbuildings.in>

Call: 1-800-103-0339

Email: HBT-Indiabuildings@honeywell.com

Honeywell HBT India Buildings

Unitech Trade Center, 5th Floor, Sector-43,

Block C, Sushant Lok Phase - I,

Gurgaon - 122002